


## Lab01

ein  $x$  für ein  $U_u$  oder ein  $\cdot$



\$\$\$

ab

## Resistance measurement

Procedure for resistance measurement:

- Set the measuring device to resistance measurement
- Connect the resistance to be measured to the corresponding sockets on the measuring device (the measuring device sockets labeled COM and  $\Omega$ )
- Read the measured value

There are different types of resistance measurement:

- **direct** resistance measurement
- **indirect** resistance measurement

## Direct resistance measurement

Determine the nominal and measured values of the resistance for  $R_1$  (brown, green, orange),  $R_2$  (yellow, violet, red),  $R_3$  (red, violet, red) and the incandescent lamp  $R_L$ . Also measure the approximate resistance  $R_K$  of your body from your right to your left hand.



Start drawing by  
clicking here

Tab. 1: Direct resistance measurement

How do you explain the deviation between  $R_{L,nominal}$  and  $R_{L,meas}$ ?

What consequences can  $R_K$  have?

Now determine the series and parallel connections of resistors  $R_1$ ,  $R_2$  and  $R_3$ .  
Specify the formulas used:

$R_{\text{serial}} =$

$R_{\text{parallel}} (= R_a || R_b) =$



Start drawing by  
clicking here

Tab. 2: Series and parallel connections

## Indirect resistance measurement

The resistances can also be determined by measuring the current/voltage.

**Ohm's law: In an electrical circuit, the current increases with increasing voltage and decreases with increasing resistance.**

$$I = \frac{U}{R}$$

Build the measuring circuit shown in [figure 1](#) for each of the three resistors and set the voltage on the power supply to 12 V.



**Start drawing by  
clicking here**

Fig. 1: Indirect resistance measurement

Measure  $U_n$  [V] and  $I_n$  [mA]. Calculate  $R_n$  [k $\Omega$ ] from these values.



**Start drawing by  
clicking here**

Tab. 3: Indirect resistance measurement

From:

<https://nuggets.mexle.te.hs-heilbronn.de/> - **MEXLE Nuggets**

Permanent link:

<https://nuggets.mexle.te.hs-heilbronn.de/doku.php?id=start>

Last update: **2026/03/09 23:26**

